



- 1 hand-held microphone transmitter (cardioid characteristic), 1 receiver, 1 plug-in PSU.
- True diversity system.
- 80 selectable UHF channels (863-865 MHz).
- ACT function for transmitting the selected frequency to the hand-held microphone via infrared signal.
- Autoscan.
- Volume and squelch controls.
- Transmitting power can be switched at the hand-held microphone (high/low).
- Indication for channel, antenna A/B, ACT status and AF audio level (receiver), channel and battery status (hand-held microphone).
- Robust metal housing (receiver).

### TECHNICAL DATA

- Carrier frequency:** 863-865MHz
- Transmitting power:** <10mW (EIRP)
- RF S/N ratio:** 105dB
- Audio range:** 50-18,000Hz,  $\pm 3$ dB
- Dynamic range:** 120dB
- THD:** <0.5%
- Audio output:** 350mV/10k ohm (jack) 25mV/10k ohm (XLR, bal.)
- Operating range:** Approx. 30m
- Admiss. ambient temp:** 0-40 °C
- Power supply:** (Transmitter) 2 x 1.5V batt. AA size (Receiver) via suppl. plug-in PSU
- Dimensions:** (Transmitter)  $\varnothing$  52mm x 275mm (Receiver) 152x38x120mm
- Weight:** (Transmitter) 235g (Receiver) 482g
- Connections:** 1 x 6.3mm jack, unbal. 1 x XLR, bal.

